

8.7 #AA0BDD

Description:

Sets the digital output value of the upper eight channels.

Command Syntax:

#AA0BDD[CS](CR)	
#	Delimiter character
AA	Address of the device to be configured in hexadecimal format (00 to FF)
0B	Command to set the digital output value of the upper 8 channels
DD	Two digit hexadecimal value. Bit 0 corresponds to DOut 0, bit 1 corresponds to DOut 1, etc. If the bit is 1, the digital output channel will be on, if the bit is 0, the digital output channel will be off.
[CS]	Checksum
(CR)	Carriage Return

Response:

Valid Command: >[CS](CR)

Invalid Command: ?[CS](CR)

Ignored Command: ![CS](CR)

>	Delimiter for a valid command
?	Delimiter for an invalid command
!	Delimiter for an ignored command
[CS]	Checksum
(CR)	Carriage Return

Examples:

Set DOut 8, DOut 9, DOut 10, DOut 11 to on, and DOut 12, DOut 13, DOut 14, DOut 15 to off and device returns a valid response.

Command: #010B0F(CR)

Response: >(CR)

Note: This command is only applicable on devices with digital output channels.