

## 8.24 @AA(Data)

Description:

Sets the digital output channel value at a specified address.

Command Syntax:

@ <u>AA</u> ( <u>Data</u> )[ <u>CS</u> ](CR)	
@	Delimiter character
<u>AA</u>	Address of the device to be configured in hexadecimal format (00 to FF)
( <u>Data</u> )	Data to be set to the digital output channels in a hexadecimal format.
[ <u>CS</u> ]	Checksum
(CR)	Carriage Return

Response:

Valid Command: >[CS](CR)

Invalid Command: ?AA[CS](CR)

>	Delimiter for a valid command
?	Delimiter for an invalid command
!	Ignore command
[ <u>CS</u> ]	Checksum
(CR)	Carriage Return

Examples:

Set output of device to 55 and return a valid command. Command sets DOut 0, DOut 2, DOut 4, DOut 6 to high and DOut 1, DOut 3, DOut 5, DOut 7 to low.

Command: @0155(CR)

Response: >(CR)

**Note:** This command is only available on devices with digital output channels.