

## 8.9 #AAcDD

### Description:

Sets the specified digital output channel from the lower eight channels.

### Command Syntax:

#AAcDD[CS](CR)	
#	Delimiter character
AA	Address of the device to be configured in hexadecimal format (00 to FF)
A	Command to set a single digital output of the lower 8 channels
c	Specifies the digital output channel to be set (0-7)
DD	00: set the digital output channel to off 01: set the digital output channel to on
[CS]	Checksum
(CR)	Carriage Return

### Response:

Valid Command: >[CS](CR)

Invalid Command: ?[CS](CR)

Ignored Command: ![CS](CR)

>	Delimiter for a valid command
?	Delimiter for an invalid command
!	Delimiter for an ignored command
[CS]	Checksum
(CR)	Carriage Return

### Examples:

Set DOut 1, to on and device returns a valid response.

Command: #01A101(CR)

Response: >(CR)

**Note:** This command is only applicable for the devices with digital output channels.