

8.8 #AA1cDD

Description:

Sets the specified digital output channel of the lower eight channels.

Command Syntax:

# <u>AA</u> 1 <u>c</u> <u>DD</u> [<u>CS</u>](<u>CR</u>)	
#	Delimiter character
<u>AA</u>	Address of the device to be configured in hexadecimal format (00 to FF)
1	Command to set a single digital output of the lower 8 channels
<u>c</u>	Specifies the digital output channel to be set (0-7)
<u>DD</u>	00: set the digital output channel to off 01: set the digital output channel to on
[<u>CS</u>]	Checksum
(<u>CR</u>)	Carriage Return

Response:

Valid Command: >[CS](CR)

Invalid Command: ?[CS](CR)

Ignored Command: ![CS](CR)

>	Delimiter for a valid command
?	Delimiter for an invalid command
!	Delimiter for an ignored command
[<u>CS</u>]	Checksum
(<u>CR</u>)	Carriage Return

Examples:

Set DOut 1, to on and device returns a valid response.

Command: #011101(CR)

Response: >(CR)

Note: This command is only applicable for the devices with digital output channels.