

8.17 \$AACN

Description:

Clears the digital input counter of the specified channel.

Command Syntax:

\$<u>AA</u>C<u>N</u>[<u>CS</u>](CR)	
\$	Delimiter character
<u>AA</u>	Address of the device to be configured in hexadecimal format (00 to FF)
C	Command to clear digital input counter
<u>N</u>	Channel to be cleared (0 to F)
[<u>CS</u>]	Checksum
(CR)	Carriage Return

Response:

Valid Command: **!AA[CS](CR)**

Invalid Command: **?AA[CS](CR)**

!	Delimiter for a valid command
?	Delimiter for an invalid command
<u>AA</u>	Address of the device which responded
[<u>CS</u>]	Checksum
(CR)	Carriage Return

Examples:

Sends command to clear the value of channel 3. Returns a valid response.

Command: **\$01C3(CR)**

Response: **!01(CR)**

Note: This command is only applicable on devices with digital input channels.