

\$aa0Ci

Applies to: ED-549

Description:

Command to perform a zero calibration on a specified channel.

Command Syntax:

\$aa0Ci[CS](CR)	
\$	Delimiter character
aa	Address of the device to be calibrated, in hexadecimal format (00 to FF)
0C	Command to perform the zero calibration
i	Channel on which to perform the zero calibration
[CS]	Checksum
(CR)	Carriage Return

Response:

Valid Command: **!aa[CS](CR)**

Invalid Command: **?aa[CS](CR)**

!	Delimiter for a valid command
?	Delimiter for an invalid command
aa	Address of the device which responded
[CS]	Checksum
(CR)	Carriage Return

Examples:

Send the command to set the zero calibration of channel 0 to the voltage being applied to the line.

Command: \$010C0(CR)

Response: !01(CR)

Note: Calibration must be enabled using ~aaEV before using this command.